Description

This switch is used to call the Nurses as per the requirements of the patients. This switch is to be installed inside the Toilet. Toilet Call Switch Push Button module comprises of recess mountable having Pull Cord for emergency call from the toilets. This bed switch consists of Nurse Call & Reset switch button. The patient should pull the cord of the Nurse call, after that as per the requirements of the patients; the Nurse should press the switch button of the Nurse call. This bed switch is also used for the satisfaction of the patients and save the timings of the nurses.

Features

- Based on Microcontroller
- Operating temperature and relative humidity
- Holder type LED indication of each call.
- Wall mounted configurations
- 12 VDC Operating Voltage
- ABS Body
- Easy and quick installation
- Networking system
- Working mode: consecutive



Electrical Specifications:

Operating Voltage 12V DC

Max PSU rating 10 mA

Indication LED indicators, Call accept / Reset, Nurse Call

User's Controls Call Accept / Reset

Nurse Call Bed switch with cord Nurse Call

Installation method Wall mounted configuration

Environmental Specifications:

Operational temperature range -0C to +60C operating

Operating Humidity ≤ 95% RH (Relative Humidity)

Mechanical Information:

Dimension Front Plate: 114mm (H) x 93mm (W)

Back Box : 4 inch (H) x 3 inch (W)

Weight Approx. 200g

Colour Cream white

Housing ABS Plastic





H.O.:19, DSIDC, Computer Complex, Scheme-1, Okhla Industrial Area, Phase-2, New Delhi-110020 (India)

Tel: +91-11-26385033, 26385390, 46515680

Email:ase99india@yahoo.co.in Web: www.dakshglobal.com Works: B-220, ELDECO, Sidcul Industrial Park, Phase-1,

<u>Sitargnj</u>, U.S. Nagar, Uttarakhand-262405 (India) Tel: +91-11-26385033, 26385390, 46515680

Mob: +91-9811937979

Email: h_kundu@dakshglobal.com, Web: www.dakshglobal.com

Note: It is essential to ensure that only known compatible components are used in a fire detection system. If in doubt, always consult the fire control panel supplier/manufacturer.